



# CX 02 B







## 2 seats for connectors


size **2 modules**

EN 61984 rating	50 V 0,8 kV 3
Rated voltage (UL / CSA)	50 V
Insulation resistance	≥ 10 GΩ
Ambient temperature limit	-40 °C ... +125 °C



ECBT2.E115072 | ECBT8.E115072

Item	Description	Part No.	Dimension
	2-seat holder for shielded connectors Male inserts, two seats for BUS connectors	<a href="#">CX 02 BM</a>	
	2-seat holder for shielded connectors Female inserts, two seats for BUS connectors	<a href="#">CX 02 BF</a>	
	Earthing adapter (optional)	<a href="#">CR GND</a>	



### Tutorial

#### Materials

Insert	polycarbonate (PC)
UL 94 flame rating	V-0
Colour	pebble grey, RAL 7032

Female and male shielded connectors fit both in female and in male holder/adapter insert.

Suitable to hold in place any combination of up to two shielded connectors

**CX 01 BC, CX 01 B, CX 04 B or CX 08 B.**

Both the female and the male inserts may accept a combination of up to two shielded connectors of any gender, as far as the correct specular assignment is set on the mating connector.

Extraction tool for BUS shielded connectors from MIXO BUS insert, see **CX BES**.

The shielded connectors have their shield insulated from the enclosure's earthing point.

If you wish to earth-connect the shield, install on the panel an anchorage for shielded cables **CR..ST** or the **CR GND** earthing adapter.

#### Accessories

#### Pages

##### MIXO Frames

Metal frames for modular units	C.95
Thermoplastic docking frames	C.98-101